



UK Technical Data o6

RK 12

Door Bell Transformer - AC output

Function

The RK Doorbell transformers generate one or more safety extra-low voltage outputs from 230V AC supply input.

Features

PTC based protection automatically limits short-circuit-currents on the output of the transformer. Meets EN 61558, certified by VDE and KEMA, with ENEC approval mark for use in the EU.

Mounting

Quick fastening to mounting rail, any installation position

Applications

RK units are suitable for intermittent operation of AC powered bell systems, lock systems and relay circuits.

Notes

Restore operation after a short-circuit by briefly disconnecting the primary power input. With small loads or no load, the output voltage may rise. Short time rated for normal door bell operation, for permanent loads we recommend using safety transformers rated for 100% duty cycle.

Accessories


Surface mounting sets RK

Technical Data

Technical Data		RK 12
Series		RK 12
Operating voltage (AC)		230 V
Operating frequency		50 Hz
Internal consumption		max. 12 W
		Load circuit
Rated voltage (AC)		4 V, 8 V, 12 V
Rated current (AC)		2 A, 2 A, 1.5 A
Rated power		max. 18 VA
Rated frequency		50 Hz
Thermal overload protection		PTC primary side
		Strain relief clamp top and bottom
Connection C1 Maximum number of conductors per terminal		2
Cross section solid		1-wire: 1.5 mm ² ... 4 mm ² ; 2-wire: 1.5 mm ² ... 2.5 mm ²
		General data
Duty cycle		short-time duty (Duty cycle ≤ 1 min bei Nennlast, 5 min at max. 20 % of nominal load)
Operating position		any
Housing type		Distributor housing, wall-mounted housing
Mounting type		Mounting rail (35 mm), Wall mounting
Housing material		Polycarbonate (PC)


Technical Data	RK 12
Protection class	IP20
Width	36 mm
Height	90 mm
Depth	65 mm
Installation depth	60 mm
Width (modules)	2
Design requirements/Standards	EN 61558-1

Dimensions



Dimensional drawing Group view

Wiring example



Wiring diagram